


GENERATOR		DHY6000SE	DHY6000SE-3
Frequency	Hz	50	50
Rated Power	kVA	5	6.3
Max. Power	kVA	5.8	7.3
Voltage	V	220	220/380
Current	A	26.4	11.1
Plugs		1x16A / 1x32A	1x16A(400)/1x16A(230)
Display		LED5/LED3	LED5/LED3
Fuel tank capacity	L	15	15
Fuel consumption @75% load	H	1.2	1.2
Sound level @ 7m	dBA	72	72
DC output	V/A	12 / 8.3	12 / 8.3
Battery (Ah)		30	30
ENGINE		D450	D450
Engine type		Diesel	Diesel
Power	hp	11	11
Start		Electric	Electric
Displacement	CC	456	456
Oil Capacity	L	1.65	1.65
ALTERNATOR		AL6	AL6-3
Power	kW	6	7.5
Power Factor		1	0.8
Voltage Regulation		AVR	AVR
DIMENSIONS & WEIGHT			
Net Weight	Kg	156	156
Gross Weight	Kg	166	166
machine size	mm	920×520×740	920×520×740
Dimensions Package	mm	960×560×790	960×560×790
Loading Capacity FCL20'/40'HQ		48/144	48/144



Optional Accessories
<p>ATS control box(50A)</p>
<p>Remote controller: 1+2 ATS sensor: 2</p>
<p>Pre-heater</p>

Electrical standard and options	DHY6000SE	DHY6000SE-3
1-phase (2×16A European sockets)	●	×
3-phase (1×16A European socket )	×	●
American;UK;Australian sockets;etc	○	○
Display LED5	●	●
Display LED3	○	○
Precise overload protection	●	●
Common overload protection	○	○
E-stop button	○	○
DC output:12V / 8.3A	●	●
Earth connection	●	●
Pre-heater	○	○
ATS sensor	○	○
Remote control	○	○
ATS control box(50A)	○	○
Mechanical standard and options		
Basic color: Pantone black C	●	●
Alternator: Steel plate Q195	●	●
Alternator: Silicon steel plate DW800	○	○
Decompression handle	●	●
Option : ○ Standard feature : ● No available : ×		

Recommended Spare Parts
<p>Air filter core</p>
<p>Fuel filter element</p>
<p>Oil filter element</p>
<p>AVR</p>
<p>Alternator brush</p>